

Ministry of Electronics & I.T., STQC Directorate

#### ELECTRONICS TEST AND DEVELOPMENT CENTRE, MOHALI



B-108, Industrial area, Phase-VIII, Mohali (PB)-160071

#### **TEST REPORT**

Report No.	Unique Lab Report No.	Dated	Page No.	
ETDC(MH)/T&M/154	ULR-TC5465181000000020P	24-10-2018	1 of 7	

1. Indentor's Address

: M/s Okaya Power Pvt. Ltd.

D-7, Udyog Nagar, Rohtak Road (Near Peeragarhi Metro Station)

New Delhi - 110041

(SRF No. 17763 dt. 20.02.2018)

2. Description of item(s)

2.1 Nomenclature : SMF / VRLA Battery (12V/42Ah)

2.2 Make/Model : Okaya/ OB-42-12

2.3 Sr. No. : Sample No.1 to 6 (Refer remarks 1)

2.4 Manufactured by : Okaya Power Pvt Ltd.

2.5 Quantity : Six

3. Sample(s) received on : 20.02.2018

4. Condition of sample(s) on receipt : Good

5. Date(s)/Period item(s) tested : 22.02.2018 to 24.10.2018

6. Location where test(s) carried out (With : ETDC Mohali

name and address)

7. Reference of test method(s) used : JIS C 8702 -1: 2009 and Indentor's.

8. Applicable product specification(s) : JIS C 8702 -1: 2009 and Indentor's.

9. Deviation(s), exclusion(s), addition(s) in : Nil

test method(s)

10. Environmental conditions

10.1 Temperature :  $25^{\circ}\text{C} \pm 10^{\circ}\text{C}$ 10.2 Humidity : 45% to 70%

11. Statement with regard to compliance

: Refer to test results (Test Data)

12. Statement on uncertainty in measurement

: Not Applicable.

13. Major Equipment Used


S. no.	Nomenclature	Make	Model	Cal. Validity
	Electronic Load	Digitronics	750W	May, 2019
	Multimeter (Digital)	Rishabh	15S	April, 2019
Marie Village	Vibration Machine	Sarswati Dynamic	SEV 100	July, 2019
	Clamp meter	Meco	3600	Nov, 2018
D VI	Measuring Tape	Freemans	15M	Nov, 2018
5.	Weighting Scale	Modern Business	SNEW-100	July, 2019
,	Stop Watch	Timeter	J-23	Feb, 2019




Approved by



Ministry of Electronics & I.T., STQC Directorate







## TEST REPORT

1	Report No.	Unique Lab Report No.	Dated	Page No.
	ETDC(MH)/T&M/154	ULR-TC5465181000000020P	24-10-2018	2 of 7

14	RESIII	TS SIIN	<b>IMARISED:</b>
17.	LEGUL		THAT TOLD.


Test Stage	Test Requirements (Cl. Ref. of specs.)	Test Condition	Test Data	Pass/ Fail (Qty.)	Uncertainty (Where applicable)
1. Visual Examination	JIS 8702-1	There shall not be any deformation of body and cracks / corrosion on the terminals of the sample (Sealed Lead Acid Battery).	No defects observed.	Pass	
2. Marking	IN TO THE				
2.1 Polarity (Cl: 4.4)	JIS-C 8702-2 (Cl. 6.1) and JIS 8702-1 (Cl. 4.4)	Positive and negative terminals of the sample shall be marked with symbols (+) and (-) respectively.	Positive: (+) with Red colour  Negative: (-) with Black colour	Pass	
2.2 Designation (Cl: 4.3)	JIS 8702-2 (Cl. 6.2) and JIS C 8702-1 (Cl. 4.3)	The sample shall be marked with relevant details: a) Type Designation b) Nominal Voltage (n x 2.0 V)	SMF / VRLA Battery 12V (6x2V)	Pass Pass	-
	th comme	c) Rated Capacity (20 Hr. rate) d) Manufacturer.	42Ah Okaya Power Pvt. Ltd.	Pass Pass	
2.3. Additional Information	JIS C 8702-1 (Cl.4.3)	Following parameters shall be determined in respect of the sample: a) Mass (Kg)	Sample No Mass(Kg)  1. 14.44 kg 2. 14.40 kg 3. 14.44 kg 4. 14.48 kg 5. 14.46 kg 6. 14.42 kg		
		b) Dimension (LxWxH)	L:195 mm W: 165 mm H: 180 mm	-	-
		c) Charging Current / Voltage	Standby Use: 13.5 V to 13.8 V Initial current: 8.4 A Cycle use: 14.6 V to 14.8 V	-	-

Tested by

Approved by



Ministry of Electronics & I.T., STQC Directorate





B-108, Industrial area, Phase-VIII, Mohali (PB)-160071

## **TEST REPORT**

Report No.	Unique Lab Report No.	Dated	Page No.
ETDC(MH)/T&M/154	ULR-TC5465181000000020P	24-10-2018	3 of 7

14	DES	TITE	TC	CIIN	IM	AR	ISED:	,
14.	T	, , , , ,				/A I \		

Test Stage	Test Requirements (Cl. Ref. of specs.)	Test Condition	Test Data	Pass/ Fail (Qty.)	Uncertainty (Where applicable)
3. Classification of Battery	JIS C 8702-2 (Cl. 7)	The sample shall either be Prismatic or Cylindrical.	Prismatic.	Pass	
4. Capacity Test (20Hrs.)	JIS C 8702-1 (Cl. 5.1 & 7.1)	The Fully charged sample shall be discharged by at a constant current of $2.1 \text{ A} \pm 2 \%$ at an ambient temperature of $25^{\circ}\text{C} \pm 2^{\circ}\text{C}$ till an end point terminal voltage of $10.5\text{V}$ (6 x 1.75V). The capacity shall be 42 Ah or more.	Sample Capacity No.  1 45.1Ah 2 45.2Ah 3 44.5Ah	Pass	
5. High Rate Discharge Test (Sample No.1)	JIS C 8702-1 (Cl. 5.2 & 7.2)	Fully charged sample shall be discharged at a constant current of 42A (20 x I <sub>20</sub> ) upto an end point terminal voltage of 9.6V (6x1.6V).	Discharge time: 31 minutes	Pass	
		The discharge duration shall be 27 minutes or more.			
6. Resistance to Vibration (Sample No. 3)	JIS C 8702-1 Cl.5.9	The sample shall be subjected to the following conditions: Frequency: 16.7Hz Amplitude: 4mm (peak to peak) Duration: 1 Hr continuous Direction: Vertical, Longitudinal and lateral (X, Y & Z) State of sample: Fully charged.	Conducted.	Pass	
		After the above test, there shall not be any deformation, mechanical damage, breaking on the sample	No visual defects deformation, mechanical damage, breaking on the sample observed.		

Tested by

Approved by



Ministry of Electronics & I.T., STQC Directorate





B-108, Industrial area, Phase-VIII, Mohali (PB)-160071

## TEST REPORT

Report No.	Unique Lab Report No.	Dated	Page No.	
ETDC(MH)/T&M/154	ULR-TC5465181000000020P	24-10-2018	4 of 7	

Test Stage	Test Requirements (Cl. Ref. of specs.)	Test Condition	Test Data	Pass/ Fail (Qty.)	Uncertainty (Where applicable)
7. Resistance to Shock (Sample No. 1)	JIS C 8702-1 Cl 5.10	The fully charged sample shall be given three falls from a height of 20cm with bottom facing downward on a flat hard wooden plate of 10 mm or more in thickness.	Conducted.	Pass	
		There shall not be any deformation, mechanical damage, breaking on the sample	No visual defects deformation, mechanical damage, breaking on the sample observed.		
8. Max. Permissible Current	JIS C 8702-1 (Cl. 5.5)	Fully charged sample shall be discharged at a constant current 200 A (40 x I <sub>20</sub> ) for 300sec.	Conducted	-	
(Sample No.3)		After the discharge, sample shall be recharged and it shall be discharged at a constant current of 200 A (40*(I <sub>20</sub> )) upto an end point terminal voltage of 8.04 V (6*1.34 V). The discharge duration shall not be less than 150 sec.	803 sec	Pass	
9. Storage Characterstics (Sample No.2)	JIS C 8702-1 (Cl. 5.4 & 7.4)	Fully charged sample shall be stored for 120 days. After the period, the capacity test shall be performed at a constant discharge current of 2.1A(I <sub>20</sub> ) upto an end point terminal voltage of 10.5V. The capacity shall not be less than 75% of the rated capacity	Capacity: 88.75%	Pass	



Ministry of Electronics & I.T., STQC Directorate

# ELECTRONICS TEST AND DEVELOPMENT CENTRE, MOHALI



B-108, Industrial area, Phase-VIII, Mohali (PB)-160071

## TEST REPORT

Γ	Report No.	Unique Lab Report No.	Dated	Page No.
-		ULR-TC5465181000000020P	24-10-2018	5 of 7

14. RESULTS SUMMARISED:

Test Stage	Test Requirements (Cl. Ref. of	Test Condition	Test Data	Pass/ Fail (Qty.)	Uncertainty (Where applicable)
10. Capacity Test After Charge Acceptance After Deep Discharge	JIS C 8702- 1 Cl. 5.6	A suitable load resistor which can draw a current of 84 A ±10% (40 x I <sub>20</sub> ) shall be connected across the fully charged sample and it shall be stored for 360Hrs. After the storage period, the load resistor shall be disconnected from the sample and sample shall be recharged at constant voltage (UC) as per 6.1A for a period of 48Hrs with Initial charging current between 16.8 A (6xI <sub>20</sub> to 10xI <sub>20</sub> ). After the charging period, the sample shall remain open circuited for 5 to 24Hrs and then shall be discharged at 5 A (C <sub>20</sub> ).  The observed capacity of the sample shall not be less than 75% of the rated capacity.	Capacity: 102%	Pass	
11. Gas Recombinating Characteristics	JIS C 8702- 1:2009 Cl. 5.10 &7.9	The sample shall be tested as under:  State of Battery: Fully Charged  Charging condition: Battery shall be charged continuously at a constant current of 2xI <sub>20</sub> for 48 Hrs.  A gas collecting device shall be installed as specified and within one hour of completion of charging as above, the battery shall be charged at a constant current of 0.1 x I <sub>20</sub> continuously Immediately after lapse of 24 hr from current passing, collection of gas shall be started.  Duration of gas collection: 5 Hrs	Efficiency of Gas Recombination: 99.4%	Pass	

Pestodby

Ruman Approved by



Ministry of Electronics & I.T., STQC Directorate

## ELECTRONICS TEST AND DEVELOPMENT CENTRE, MOHALI



B-108, Industrial area, Phase-VIII, Mohali (PB)-160071

#### **TEST REPORT**

Report No.	Unique Lab Report No.	Dated	Page No.
ETDC(MH)/T&M/154	ULR-TC5465181000000020P	24-10-2018	6 of 7

#### 15. Additional Remarks:

1. Serial Number of the samples-

Sample No	Serial No	
1	IAAHS02201051714	
2	IAAHS02201051716	
3	IAAHS02201051717	
4	IAAHS02201051718	
5 IAAHS022010517		
6 IAAHS0220105172		

2. Device Under Test (DUT) photograph enclosed as Annexure-1.

Tested by


Removed by

जगदीज कुनार/JAGDISH KUMAR वैज्ञानिक 'जि'/Scientist 'D' कंपार एवं कुनन प्रौद्योगिकी नंजालय Ministry of Comm. & Info, Technology

Ministry of Comm. के Info. Technology जारत बरकार, एसटीवन्युकी कार्यक्टोरेट, ईटीडीकी, नोडाली (पंजाब) Govt of India, STQC Directorate Centre, ETDC, Mohali (Pb.)



Ministry of Electronics & I.T., STQC Directorate





B-108, Industrial area, Phase-VIII, Mohali (PB)-160071

#### **TEST REPORT**

Report No.	Unique Lab Report No.	Dated	Page No.
ETDC(MH)/T&M/154	ULR-TC5465181000000020P	24-10-2018	7 of 7

Annexure-I



Figure-I



Figure-II

Issued by (Customer Service Cell)